




Microstrip Attenuator With Sleeve

◆Features and Electrical specifications:

Model	RFTXX-05TA7265-12.4 (XX=Attenuation value)		
Resistance Range	50 Ω		
Frequency Range	DC~12.4GHz		
Power	5 W		
Attenuation(dB)	01-10	11-20	21-30
Attenuation Tolerance(dB)	±0.6	±0.7	±1.0
VSWR	1.25 type 1.3 max		
Sleeve Material	Al (Conductive oxidation natural color)		
Temperature Coefficient	<150ppm/°C		
Substrate material	BeO		
Resistance Process	Thick Film		
Operating Temperature	-55 to +125°C (See de Power De-rating)		
ROHS Compliant	Yes		

◆Outline Drawing (Unit: mm/inch):



Diameter tolerance: ±0.05, length tolerance: ± 0.05

RFTYT Technology Co., LTD.

<http://www.rfyt.com>

E-mail: jackson@rfyt.com

cerman@rfyt.com

TEL: +86-13088268828

FAX: +86-816-2846565


218# Wenwu Middle Road, Jinkai District, Mianyang, Sichuan Province China

Ready For Tackling Your Trouble




◆ Typical Performance:


1dB Graph




2dB Graph




3dB Graph




5dB Graph



10dB Graph




15dB Graph






20dB Graph




30dB Graph




◆Use Attention:

- Elastic contact is used at the contact point between the connector and the sleeve electrode;
 - The inner hole of the radiator should match the diameter of the sleeve, and the tolerance should not be too large;
- Operation steps:
- Tighten one end of the connector with a thread to one end of the radiator;
 - Place the sleeve type attenuation plate into the internal hole of the radiator;
 - Then tighten the connector on the other end with a thread
 - Attention: Thread requires the use of thread sealant

◆Power De-rating:



◆P/N Designation:





◆Notes:

- The sleeve and radiator need to be tightly connected to ensure heat dissipation.
- Good grounding is required to ensure S parameters.
- In order to meet the requirements of the drawings, it is necessary to install radiators of sufficient size.
- If necessary, increase air cooling or water cooling.
- The connection between the connector and the sleeve type attenuation electrode must use elastic contact.
- If the sleeve is marked with "IN", be sure to place one end of the IN on the input port, and if there is no label, it will be bidirectional.

◆Remarks:

- We can provide customized RF attenuators, RF resistors, coaxial dummy (termination) loads, and mismatched dummy (termination) loads.